

**Overview**

Terminal connectors are used to connect tap conductor to power equipment to wall bushing of substation aluminium connectors are also used to connect the tap conductor of T-connector.

**Parameter**

Type	Suitable Conductor(mm <sup>2</sup> )	Main Dimension(mm)				
	Type	A	B	D	L1	L2
SYG-50	LGJ-50	30	5	18	60	60
SYG-70	LGJ-70	40	5	22	70	70
SYG-95	LGJ-95	40	5	26	80	70
SYG-120	LGJ-120	50	5	26	80	80
SYG-150	LGJ-150	50	5	30	90	80
SYG-185	LGJ-185	50	6.3	32	90	80
SYG-240/30A	LGJ-240/30	50	6.3	36	100	80
SYG-300/15A	LGJ-300/15	63	8	40	110	100
SYG-300/20A	LGJ-300-20	63	8	40	110	100
SYG-300/25A	LGJ-300/25	63	8	40	110	100
SYG-300/40A	LGJ-300/40	63	8	40	110	100
SYG-400/20A	LGJ-400/20	63	8	45	120	100
SYG-400/25A	LGJ-400/25	63	8	45	120	100
SYG-400/35A	LGJ-400/35	63	8	45	120	100
SYG-400/50A	LGJ-400/50	63	8	45	120	100
SYG-500/35A	LGJ-500/35	80	8	52	130	100
SYG-500/45A	LGJ-500/45	80	8	52	130	100
SYG-500/65A	LGJ-500/65	80	8	52	130	100
SYG-630/45A	LGJ-630/45	100	10	60	150	100
SYG-630/55A	LGJ-630/55	100	10	60	150	100
SYG-630/80A	LGJ-630/80	100	10	60	150	100
SYG-800/55A	LGJ-800/55	125	12.5	65	170	125
SYG-800/70A	LGJ-800/70	125	12.5	65	170	125
SYG-800/100A	LGJ-800/100	125	12.5	65	170	125